







## RS6x Series Technical Accessory Guide








NOTE: This document is only for general reference. Solutions Pathway and related PMBs should be used for product availability, pricing, and final solution selection.






\* Zebra does not endorse or specifically recommend any **third-party products, accessories, or hardware**. ZEBRA DISCLAIMS ANY AND ALL LIABILITY, INCLUDING ANY EXPRESS OR IMPLIED WARRANTIES, WHETHER ORAL OR WRITTEN, FOR SUCH THIRD PARTY PRODUCTS, ACCESSORIES, OR HARDWARE. THE CUSTOMER ACKNOWLEDGES THAT NO REPRESENTATION HAS BEEN MADE BY ZEBRA AS TO THE FITNESS OF THE THIRD-PARTY PRODUCTS, ACCESSORIES, OR HARDWARE FOR THE CUSTOMER'S INTENDED PURPOSE.

### Cradles/Charging

Part Number	Picture	Description	Notes	Required Items
CRD-NGRS-1S1BU-01		Single Slot Cradle	<ul style="list-style-type: none"> <li>▶ Provides USB support</li> <li>▶ Supports scanner and spare battery charging</li> <li>▶ LED notification of spare battery charging status.</li> </ul>	<ul style="list-style-type: none"> <li>▶ Power Supply (PWR-BGA12V50W0WWW and CBL-DC-388A1-01)</li> <li>▶ AC Line Cord (23844-00-00R).</li> <li>▶ Also requires Micro USB Cable (25-124330-01R) for host communication.</li> </ul>
CRD-NWTRS-2SUCH-01		Single Slot Cradle for WT6x and RS6x	<ul style="list-style-type: none"> <li>▶ Provides USB support to WT6x and RS6x</li> <li>▶ Supports WT6x and RS6x</li> <li>▶ Does not support spare battery charging</li> <li>▶ LED notification of spare battery charging status.</li> </ul>	<ul style="list-style-type: none"> <li>▶ Power Supply (PWR-BGA12V50W0WWW and CBL-DC-388A1-01)</li> <li>▶ AC Line Cord (23844-00-00R).</li> <li>▶ Also requires Micro USB Cable (25-124330-01R) for host communication.</li> </ul>
CRD-NGRS-5S5BC-01		5-Slot Charge Only Cradle + Spare Battery Charging	<ul style="list-style-type: none"> <li>▶ Charges 5 scanners and 5 spare batteries</li> <li>▶ Can also be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01)</li> </ul>	<ul style="list-style-type: none"> <li>▶ DC Line Cord (CBL-DC-382A1-01) and Power Supply (PWR-BGA12V108W0WWW)</li> <li>▶ AC Line Cord (23844-00-00R)</li> </ul>
CRD-NGRS-10SCH-01		10-Slot Charge Only Cradle	<ul style="list-style-type: none"> <li>▶ Charges 10 scanners</li> <li>▶ Does not charge spare batteries</li> <li>▶ Can also be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01)</li> </ul>	<ul style="list-style-type: none"> <li>▶ DC Line Cord (CBL-DC-382A1-01) and Power Supply (PWR-BGA12V108W0WWW)</li> <li>▶ AC Line Cord (23844-00-00R)</li> </ul>

CRD-10NG-GRD-01		10-Slot Charge Only Cradle Kit	<ul style="list-style-type: none"> <li>▶ Charges 10 scanners</li> <li>▶ Does not charge spare batteries</li> <li>▶ Can also be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01).</li> <li>▶ Kit includes 10-Slot Charge Only Cradle(CRD-NGRS-10SCH-01), Power Supply (PWR-BGA12V108W0WW), DC Line Cord (CBL-DC-382A1-01) and AC Line Cord (23844-00-00R).</li> <li>▶ <b>NOTE: This is a custom product. Please work with your Zebra representative to open a Custom Product Request (CPR) if you would like to order this item.</b></li> </ul>	
CRD-NWTRS-10SCH-01		10-Slot Charge Only Cradle for WT6x and RS6x	<ul style="list-style-type: none"> <li>▶ Charges 5 WT6x units and 5 RS6x units</li> <li>▶ Does not charge spare batteries</li> <li>▶ Can also be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01)</li> </ul>	<ul style="list-style-type: none"> <li>▶ DC Line Cord (CBL-DC-382A1-01) and Power Supply (PWR-BGA12V108W0WW)</li> <li>▶ AC Line Cord (23844-00-00R)</li> </ul>
CRD-10NW-GRD-01		10-Slot Charge Only Cradle for WT6x and RS6x Kit	<ul style="list-style-type: none"> <li>▶ Charges 5 WT6x units and 5 RS6x units</li> <li>▶ Does not charge spare batteries</li> <li>▶ Can also be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01).</li> <li>▶ Kit includes 10-Slot Charge Only Cradle for WT6x and RS6x(CRD-NWTRS-10SCH-01), Power Supply (PWR-BGA12V108W0WW), DC Line Cord (CBL-DC-382A1-01) and AC Line Cord (23844-00-00R).</li> <li>▶ <b>NOTE: This is a custom product. Please work with your Zebra representative to open a Custom Product Request (CPR) if you would like to order this item.</b></li> </ul>	
CRD-8NW-GRD-01		8-Slot Charge Only Cradle for WT6x, RS6x and Spare Batteries Kit	<ul style="list-style-type: none"> <li>▶ Charges 4 WT6x units, 4 RS6x units and 4 Spare WT6x/RS6x Spare Batteries</li> <li>▶ Can also be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01).</li> <li>▶ Kit includes 8-Slot Charge Only Cradle for WT6x, RS6x and Spare Batteries (CRD-NWTRS-8SC4B-01), Power Supply (PWR-BGA12V108W0WW), DC Line Cord (CBL-DC-382A1-01) and AC Line Cord (23844-00-00R).</li> <li>▶ <b>NOTE: This is a custom product. Please work with your Zebra representative to open a Custom Product Request (CPR) if you would like to order this item.</b></li> </ul>	
CRD-NGRS-5S5BE-01		5-Slot Ethernet + Charge Cradle with Spare Battery Charging	<ul style="list-style-type: none"> <li>▶ to be discontinued 2/2021, see PMB 10520</li> <li>▶ Allows Ethernet speeds up to 1 Gb</li> <li>▶ Charges 5 scanners and 5 spare batteries</li> <li>▶ Can also be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01)</li> </ul>	<ul style="list-style-type: none"> <li>▶ DC Line Cord (CBL-DC-382A1-01) and Power Supply (PWR-BGA12V108W0WW)</li> <li>▶ AC Line Cord (23844-00-00R)</li> </ul>

SAC-NWTRS-4SCH-01		4-Slot Battery Charger	<ul style="list-style-type: none"> <li>▶ Charges up to 4 Spare Batteries</li> <li>▶ Up to 4 Battery Chargers can be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01)</li> </ul>	<ul style="list-style-type: none"> <li>▶ Power Supply (PWR-BGA12V50W0WW and CBL-DC-388A1-01)</li> <li>▶ AC Line Cord (23844-00-00R).</li> </ul>
SACWT60-4-WM		4-Slot Battery Charger Kit with AC Line Cord	<ul style="list-style-type: none"> <li>▶ Charges up to 4 Spare Batteries</li> <li>▶ Up to 4 Battery Chargers can be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01).</li> <li>▶ Kit includes 4-Slot Battery Charger (SAC-NWTRS-4SCH-01), Power Supply (PWR-BGA12V50W0WW), DC Line Cord (CBL-DC-388A1-01) and AC Line Cord (23844-00-00R).</li> <li>▶ NOTE: This is a custom product. Please work with your Zebra representative to open a Custom Product Request (CPR) if you would like to order this item.</li> </ul>	
SACWT60-4-WM-INT		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> <li>▶ Charges up to 4 Spare Batteries</li> <li>▶ Up to 4 Battery Chargers can be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01).</li> <li>▶ Kit includes 4-Slot Battery Charger (SAC-NWTRS-4SCH-01), Power Supply (PWR-BGA12V50W0WW) and DC Line Cord (CBL-DC-388A1-01).</li> <li>▶ NOTE: This is a custom product. Please work with your Zebra representative to open a Custom Product Request (CPR) if you would like to order this item.</li> </ul>	▶ AC Line Cord (23844-00-00R)
SAC-NWTRS-20SCH-01		20-Slot Battery Charger	<ul style="list-style-type: none"> <li>▶ Charges up to 20 Spare Batteries</li> <li>▶ Can be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01)</li> </ul>	<ul style="list-style-type: none"> <li>▶ DC Line Cord (CBL-DC-382A1-01) and Power Supply (PWR-BGA12V108W0WW)</li> <li>▶ AC Line Cord (23844-00-00R)</li> </ul>
SAC-20SLOT-GRD-01		20-Slot Battery Charger Kit	<ul style="list-style-type: none"> <li>▶ Charges up to 20 Spare Batteries</li> <li>▶ Can be wall or rack mounted using Mounting Bracket (BRKT-SCRD-SMRK-01).</li> <li>▶ Kit includes 20-Slot Battery Charger (SAC-NWTRS-20SCH-01), DC Line Cord (CBL-DC-382A1-01), Power Supply (PWR-BGA12V108W0WW) and AC Line Cord (23844-00-00R).</li> <li>▶ NOTE: This is a custom product. Please work with your Zebra representative to open a Custom Product Request (CPR) if you would like to order this item.</li> </ul>	




BRKT-SCRD-SMRK-01		Multi-Slot Wall/Rack Mount Bracket	<ul style="list-style-type: none"> <li>▶ Allows for rack and wall mounting of one 5-Slot, 10-Slot, or 20-Slot Charger. Also can be used to mount up to four Single Slot Cradles or 4-Slot Battery Chargers</li> <li>▶ Bracket can be mounted on standard 19" network rack or on a wall.</li> <li>▶ Cable routing slots &amp; removable power supply holder tray.</li> <li>▶ Adjustable tabs &amp; screw mounts for easy hanging/installation.</li> <li>▶ Adjustable orientations - horizontal, vertical, angled.</li> <li>▶ See the Bluetooth-Generic Accessories TAG for info on 3rd party Network Racks that can be used for mounting this bracket.</li> </ul>	
ADP-TC7X-PLT-FX		5-Slot ShareCradle Mounting Bracket Adapter Plate for Honeywell	<ul style="list-style-type: none"> <li>▶ Allows Zebra Multi-Slot ShareCradles to be mounted on legacy Honeywell Flex Cradle Wall Mount Brackets (HON SKU #203-641-002).</li> <li>▶ Includes hardware to attach plate to HON wall bracket and secure ShareCradle to plate.</li> <li>▶ <b>NOTE: This is a custom product. Please work with your Zebra representative to open a Custom Product Request (CPR) if you would like to order this cable.</b></li> </ul>	
STB3678-C100F3WW  STB3678-C100F3CN (for use in mainland China only)		Communication Cradle	<ul style="list-style-type: none"> <li>▶ Allows RS6x to be easily connected with hosts that do not have a Bluetooth radio for direct communication.</li> <li>▶ Pairing barcode on Cradle is scanned to instantly pair with the RS6x.</li> <li>▶ Up to 7 scanners can be paired per cradle.</li> <li>▶ <b>NOTE: RS6x may require updated firmware to support communication with the cradle.</b></li> </ul>	<ul style="list-style-type: none"> <li>▶ Host communication cable and possibly a power supply depending on the host cable type.</li> <li>See 36XX Series Scanner accessory document for cable and power supply options</li> </ul>
FLB3678-C100F3WW  FLB3678-C100F3CN (for use in mainland China only)		Sealed Communication Cradle	<ul style="list-style-type: none"> <li>▶ Allows RS6x to be easily connected with hosts that do not have a Bluetooth radio for direct communication.</li> <li>▶ Pairing barcode on Cradle is scanned to instantly pair with the RS6x.</li> <li>▶ IP65 sealed for installations requiring wash-down (i.e. forklift installations).</li> <li>▶ Up to 7 scanners can be paired per cradle.</li> <li>▶ <b>NOTE: RS6x may require updated firmware to support communication with the cradle.</b></li> </ul>	<ul style="list-style-type: none"> <li>▶ Host communication cable and possibly a power supply depending on the host cable type.</li> <li>See 36XX Series Scanner accessory document for cable and power supply options</li> </ul>
<b>Communication Cables</b>				
Part Number	Picture	Description	Notes	Required Items
25-124330-01R		USB Cradle to PC/Host cable	▶ Micro USB connection on cradle end	

Soft Goods				
Part Number	Picture	Description	Notes	Required Items
SG-NGRS-TRGA-01		Replacement Trigger Swivel assembly - <u>Velcro</u> finger strap	<ul style="list-style-type: none"> <li>▶ Used with RS6000 units that use the Velcro finger strap</li> <li>▶ Strap and buckle sold separately</li> </ul>	
SG-NGRS-TRGA-02		Replacement Trigger Swivel assembly - <u>Nylon</u> finger strap	<ul style="list-style-type: none"> <li>▶ Used with RS6000 units that use the Nylon finger strap.</li> <li>▶ Nylon finger straps are an alternative to the standard Velcro finger straps and are specifically designed for warehouse and manufacturing environments where the RS6000 finger straps are subjected to high abrasion.</li> <li>▶ Nylon straps deliver better durability and longer life than the Velcro finger straps and offer the following features: <ul style="list-style-type: none"> <li>• Resistance to finger strap abrasion, caused by frequent handling of packages and other objects with rough surfaces.</li> <li>• Adjustability of the nylon finger strap via a metal buckle, to accommodate a wide range of finger sizes.</li> <li>• A comfortable and secure fit, even while wearing gloves.</li> </ul> </li> <li>▶ Metal CAM Buckle is included on the Trigger Swivel assembly.</li> <li>▶ Strap (SG-NGRS-STRPNY-10) sold separately</li> </ul>	If converting RS6000 from Velcro to Nylon strap, also order Nylon Straps (SG-NGRS-STRPNY-10)
SG-NGRS-TRLH-01		Replacement Triggerless Strap Holder assembly	<ul style="list-style-type: none"> <li>▶ Strap and buckle sold separately</li> </ul>	
SG-NGRS-CMPD-01		Replacement Comfort Pads	<ul style="list-style-type: none"> <li>▶ Works on both trigger and triggerless configurations</li> <li>▶ Includes Main and Rear comfort pads</li> </ul>	
SG-NGRS-STRPKV-10		Replacement Straps for Trigger configuration - <u>Velcro</u> finger strap (pack of 10)	<ul style="list-style-type: none"> <li>▶ Use with RS6x units that have a trigger.</li> <li>▶ Uses Velcro and updated hypalon materials vs. SG-NGRS-STRPK-10.</li> </ul>	
SG-NGRS-STRPK-10		Replacement Straps for Trigger configuration - <u>Velcro</u> finger strap (pack of 10)	<ul style="list-style-type: none"> <li>▶ Discontinued 2/2017, now use SG-NGRS-STRPKV-10 - PMB 2932.</li> <li>▶ Use with RS6x units that have a trigger.</li> </ul>	

SG-NGRS-STRPNY-10		Replacement Straps for Trigger configuration - <u>Nylon</u> finger strap (pack of 10)	<ul style="list-style-type: none"> <li>▶ Use with RS6x units that have a trigger AND use Nylon strap/CAM Buckle design.</li> <li>▶ Includes finger mount pad.</li> <li>▶ Uses Nylon materials.</li> <li>▶ Nylon straps deliver better durability and longer life than the Velcro finger straps and offer the following features: <ul style="list-style-type: none"> <li>• Resistance to finger strap abrasion, caused by frequent handling of packages and other objects with rough surfaces.</li> <li>• Adjustability of the nylon finger strap via a metal buckle, to accommodate a wide range of finger sizes.</li> <li>• A comfortable and secure fit, even while wearing gloves.</li> </ul> </li> </ul>	If converting RS6000 from Velcro to Nylon strap, also order Replacement Trigger Assembly for Nylon straps (SG-NGRS-TRGA-02)
SG-NGRS-STRP2VK-10		Replacement Straps for Triggerless configuration - Velcro finger strap (pack of 10)	<ul style="list-style-type: none"> <li>▶ Use with RS6x units that do not have a trigger (triggerless configuration).</li> <li>▶ Uses velcro and updated hypalon materials vs. SG-NGRS-STRPK2-10.</li> </ul>	
SG-NGRS-STRPK2-10		Replacement Straps for Triggerless configuration - Velcro finger strap (pack of 10)	<ul style="list-style-type: none"> <li>▶ Discontinued 2/2017, now use SG-NGRS-STRP2VK-10 - PMB 2932</li> <li>▶ Use with RS6x units that do not have a trigger (triggerless configuration)</li> </ul>	
SG-NGRS-STBKLV-10		Replacement Strap Buckles (pack of 10)	<ul style="list-style-type: none"> <li>▶ Use one buckle with triggered configuration and two with triggerless configuration</li> <li>▶ Used with Replacement Straps that use Velcro material (SG-NGRS-STRPKV-10 and SG-NGRS-STRP2VK-10).</li> </ul>	
SG-NGRS-STBKL-10		Replacement Strap Buckles (pack of 10)	<ul style="list-style-type: none"> <li>▶ Discontinued 2/2017, now use SG-NGRS-STBKLV-10 - PMB 2932</li> <li>▶ Use one buckle with triggered configuration and two with triggerless configuration.</li> <li>▶ Used with Replacement Straps that use Velcro material (SG-NGRS-STRPK-10 and SG-NGRS-STRPK2-10).</li> </ul>	
AF2820DW (3rd party) *  <a href="http://www.ultimacase.com">http://www.ultimacase.com</a>		Wrist Mount	<ul style="list-style-type: none"> <li>▶ Allows RS6x to be worn on wrist or back of hand.</li> <li>▶ Requires triggerless RS6x configuration.</li> </ul>	





**Power Cords/Power Supplies**



Part Number	Picture	Description	Notes	Required Items
CBL-DC-388A1-01		DC Power Cord	<ul style="list-style-type: none"> <li>▶ Used along with Power Supply PWR-BGA12V50W0WW to power Single Slot Cradle and 4-Slot Battery Charger.</li> <li>▶ Cable length is 1.8 meters</li> </ul>	
PWR-BGA12V50W0WW		Power Supply	<ul style="list-style-type: none"> <li>▶ Used to power Single Slot Cradle and 4-Slot Battery Charger.</li> <li>▶ 100-240 VAC, 12V, 4.16A, 50W</li> <li>▶ Provides US DOE Level VI compliance for power efficiency.</li> <li>▶ Replaces PWRS-14000-148R</li> </ul>	DC Line Cord (CBL-DC-388A1-01) and AC Line Cord (23844-00-00R)
KIT-PWR-12V50W		Power Supply Kit	<ul style="list-style-type: none"> <li>▶ Includes Power Supply (PWR-BGA12V50W0WW) and DC Line Cord (CBL-DC-388A1-01)</li> </ul>	AC Line Cord (23844-00-00R)
PWRS-14000-148R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> <li>▶ Discontinued 1/2017, now use PWR-BGA12V50W0WW and CBL-DC-388A1-01 - see PMB 2923 and PMB 2851.</li> <li>▶ Replaces KT-14000-148R</li> <li>▶ Used to power Single Slot Cradle and 4-Slot Battery Charger</li> <li>▶ 100-240 VAC, 12VDC, 3.33A</li> <li>▶ Energy Star Compliant</li> </ul>	23844-00-00R
50-14000-148R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> <li>▶ Discontinued 12/2007 - replaced by KT-14000-148R</li> <li>▶ Used to power Single Slot Cradle and 4-Slot Battery Charger</li> </ul>	23844-00-00R
KT-14000-148R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> <li>▶ Replaces 50-14000-148R</li> <li>▶ Used to power Single Slot Cradle and 4-Slot Battery Charger</li> <li>▶ Discontinued 12/2010 - now use PWRS-14000-148R</li> </ul>	23844-00-00R
CBL-DC-381A1-01		DC Power Cord	<ul style="list-style-type: none"> <li>▶ Used to power 5-Slot ShareCradles when using Level VI Efficiency power supply (PWR-BGA12V108W0WW)</li> <li>▶ This cable does not include the black extension release latch which is not required when used on Multi-Slot ShareCradles.</li> <li>▶ CBL-DC-382A1-01 is still typically used though.</li> </ul>	
CBL-DC-382A1-01		DC Power Cord	<ul style="list-style-type: none"> <li>▶ Used with Power Supply PWR-BGA12V108W0WW to power 5-Slot, 10-Slot, 20-Slot Cradles</li> </ul>	
50-16002-029R		DC Power Cord	<ul style="list-style-type: none"> <li>▶ Used with Power Supply PWRS-14000-241R to power 5-Slot, 10-Slot, 20-Slot Cradles</li> <li>▶ Discontinued 2/2017, now use CBL-DC-382A1-01 - PMB 2851 and 2933</li> </ul>	
PWR-BGA12V108W0WW		Power Supply	<ul style="list-style-type: none"> <li>▶ Used to power 5-Slot, 10-Slot, 20-Slot Cradles</li> <li>▶ 100-240 VAC, 12V, 9A, 108W</li> <li>▶ Provides US DOE Level VI compliance for power efficiency.</li> <li>▶ Replaces PWRS-14000-241R</li> </ul>	CBL-DC-382A1-01 and 23844-00-00R

PWRS-14000-241R		Power Supply	<ul style="list-style-type: none"> <li>▶ Replaces 50-14000-241R</li> <li>▶ Used to power 5-Slot, 10-Slot, 20-Slot Cradles</li> <li>▶ 100-240VAC, 12VDC, 9A</li> <li>▶ Energy Star Compliant</li> <li>▶ Discontinued 2/2017, now use PWR-BGA12V108W0WW - PMB 2851 and 2933</li> </ul>	50-16002-029R and 23844-00-00R
50-14001-004R		Power Supply	<ul style="list-style-type: none"> <li>▶ Discontinued 12/2007 - replaced by 50-14000-241R</li> <li>▶ Used to power 5-Slot, 10-Slot, 20-Slot Cradles</li> </ul>	50-16002-029R and 23844-00-00R
50-14000-241R		Power Supply	<ul style="list-style-type: none"> <li>▶ Replaces 50-14001-004R</li> <li>▶ Used to power 5-Slot, 10-Slot, 20-Slot Cradles</li> <li>▶ Discontinued 12/2010 - now use PWRS-14000-241R</li> </ul>	50-16002-029R and 23844-00-00R
23844-00-00R		AC Line Cord	▶ This AC Line Cord is for use in North America. See the <b>AC Line Cords by Country</b> TAG for comparable line cords to use in other countries.	

## Batteries

Part Number	Picture	Description	Notes	Required Items
BTRY-NWTRS-33MA-02 BTRY-NWTRS-33MA-IN (for use in India)		Spare Battery with PowerPrecision+ (3350 mAh) 	<ul style="list-style-type: none"> <li>▶ Has improved battery latching mechanism vs. BTRY-NWTRS-33MA-01.</li> <li>▶ Designed, manufactured &amp; tested to meet rigorous controls &amp; standards</li> <li>▶ Premium-grade cells with higher capacity &amp; longer life cycle</li> <li>▶ Designed to help prevent overcharging &amp; electrical shock</li> <li>▶ Strong &amp; robust housing for optimal performance &amp; durability</li> <li>▶ Information available: <ul style="list-style-type: none"> <li>- Available charge status</li> <li>- Total charge accumulated on the battery</li> <li>- Basic state of health</li> </ul> </li> </ul>	
BTRY-NWTRS-33MA-01		Spare Battery with PowerPrecision+ (3350 mAh) 	<ul style="list-style-type: none"> <li>▶ Discontinued 3/2018, now use BTRY-NWTRS-33MA-02, PMB 3115</li> <li>▶ Designed, manufactured &amp; tested to meet rigorous controls &amp; standards</li> <li>▶ Premium-grade cells with higher capacity &amp; longer life cycle</li> <li>▶ Designed to help prevent overcharging &amp; electrical shock</li> <li>▶ Strong &amp; robust housing for optimal performance &amp; durability</li> <li>▶ Information available: <ul style="list-style-type: none"> <li>- Available charge status</li> <li>- Total charge accumulated on the battery</li> <li>- Basic state of health</li> </ul> </li> </ul>	